









Brushless DC Gearmotors for Class I/Div. 2 Hazardous Locations

Type 34B/SR-WX BLDC Gearmotors with Built-In Speed Controls

Our 34B4/SR-WX INTEGRAmotors™ meet NEC Class I, Division 2 standards for use in environments where flammable gases or vapors may accidentally be spilled or leak into the operating area. Available as standard products, they combine a PWM speed control, a brushless DC motor and a high-torque gearhead in one compact package.

Class I. Division 2 Construction

- Suitable for environments where flammable vapors may occasionally be present
- Upgraded terminal boxes, gasket material and bushings
- Specially coated commutator assembly
- Control board coated for outdoor applications

34B4-WX Gearmotor Features

- High starting torque; linear speed-torque characteristics
- Ideal for variable speed applications
- Zero maintenance, lasts longer than brush-type DC motors
- · All steel helical gears, synthetic lubricant
- No carbon dust from brushwear, no brushes to replace

INTEGRA Control Features

- 12 or 24 VDC rated models
- Inputs for run, brake, speed and direction
- 12 pulse/revolution tach output
- Dynamic braking for quick stops
- Current limit protects motor from overload







Typical Applications

Ideal for low-voltage automation systems, and for portable or remote applications where connection to an AC line is not possible. Also suitable for solar or battery powered equipment such as pumps, and automatic gate openers.

Type 34B/SR-WX INTEGRAmotor Gearmotor (Rating for Either 12 or 24 VDC Version)

| | | HP | | | Control Radial Continuo | | | | | |
|----------------|--------------------------|------------------|------------------|------------------|----------------------------|------------------|------------------|-----------------|---------------------|---------------------|
| Speed (rpm) | Rated Torque (lb-in.) | 12 VDC Models | 24 VDC Models | Gear Ratio: 1 | Load (Ibs) | 12 VDC Models | 24 VDC Models | Product Type | 12 VDC Model No. | 24 VDC Model No. |
| 8 | 205 | 1/5 | 1/4 | 312 | 130 | 19.0 | 11.0 | 34B4BEBL/SR-WX4 | 3293 | 3893 |
| 15 | 200 | | | 172 | 130 | | | 34B4BEBL/SR-WX4 | 3292 | 3892 |
| 26 | 185 | | | 98 | 140 | | | 34B4BEBL/SR-WX4 | 3290 | 3890 |
| 38 | 190 | | | 66 | 140 | | | 34B4BEBL/SR-WX3 | 3288 | 3888 |
| 46 | 185 | | | 55 | 130 | | | 34B4BEBL/SR-WX3 | 3287 | 3887 |
| 57 | 157 | | | 44 | 130 | | | 34B4BEBL/SR-WX3 | 3286 | 3886 |
| 84 | 106 | | | 30 | 160 | | | 34B4BEBL/SR-WX3 | 3285 | 3885 |
| 123 | 77 | | | 20 | 60 | | | 34B4BEBL/SR-WX2 | 3284 | 3884 |
| 181 | 46 | | | 14 | 65 | | | 34B4BEBL/SR-WX2 | 3283 | 3883 |
| 266 | 31 | | | 9 | 80 | | | 34B4BEBL/SR-WX2 | 3282 | 3882 |
| 455 | 18 | | | 6 | 90 | | | 34B4BEBL/SR-WX2 | 3280 | 3880 |
| 658 | 9 | | | 4 | 65 | | | 34B4BEBL/SR-WX2 | 3279 | 3879 |













Brushless DC Gearmotors for Class I/Div. 2 Hazardous Locations

Type 34B/SR-WX BLDC Gearmotors with Built-In Speed Controls





Optional Accessory Mounting bracket, model 0970 **Gearmotor Weight** approximately 9 lbs.



Bodine offers over 1,400 standard gearmotors, motors and systemmatched speed controls.

Visit bodine-electric.com for all your motion control needs.

Bodine offers the widest selection of variable-speed AC, permanent magnet DC and brushless DC fractional horsepower gearmotors and motors in the industry. For complete specifications, 2D/3D CAD drawings, or to order online, visit bodine-electric.com.